

**Mains electricity**

230 V/50 Hz

**Standby power**

0.3 W

**External operating temperature**

-20 to +35 °C

**Dimensions**

Mounting plate 71x71 mm

Built-in depth 28 mm

Built-in dimensions 51x48 mm

Shaft diameter 4 mm/6 mm

**Load type**

Trailing edge

Leading edge

**Protection**

Overtemperature software

Overtemperature hardware

Overload software

**Radio**

2.4 GHz mesh

Bluetooth®

<10 dBm

**Radio range**

Approx. 10 m indoors

The Plejd mesh technology extends the range by allowing the units to communicate with each other.

**RISK OF INJURY TO PERSON OR PROPERTY**

All work on the appliance must be carried out by an authorized electrician. National laws and regulations must be followed.

**Compliant to standards**

Hereby, Plejd AB declares that the radio equipment type VRI-03 is in compliance with Directive 2014/53/EU.

The full text of the EU declaration of conformity and third-party licenses are available at the following internet address: [plejd.com/compliance](https://plejd.com/compliance)

Plejd AB, Krokslätts Fabriker 27A  
431 37 Mölndal, Sweden

**Important information**

Do not use the product if it has visible signs of damage.

**Disposal and recycling**


This electrical product should not be disposed of together with other household waste. Contact your local recycling center for guidance on electrical and electronic equipment disposal.



plejd

## VRI-03

### INSTALLATION MANUAL



Further information can be found in the **Plejd** app or at **[plejd.com](https://plejd.com)**


## NOTE!

During installation the product is non-dimmable.  
Use the app to configure before use.

### 1 Connect the product

Install the product in the appliance box and connect it following the wiring diagram.

VRI-03 is a combination of the products RTR-02 and DIM-01.



#### Control inputs 1 2

Control inputs 1 and 2 can be used for control using e.g. motion sensor (with neutral conductor). The inputs can also be used to wirelessly control one or more products from Plejd. Double clicking the dial can be used for controlling a scene.

### 2 Install frame, center plate and dial



Use the included accessories to install your chosen frame, center plate and dial:

- Nut
- Shaft adapter

### 2 Follow the instructions in the app

Download the Plejd app on the App Store or Google Play. After supplying power to the device by following the wiring diagram, use the app to complete the installation. Setup requires Bluetooth® and an internet connection.

### 3 Hand over the Plejd system

Once you have completed the installation, you will find the system code in the app. Write the code on the included sticker . Place the sticker in the distribution box and give the welcome folder  to the customer.

#### Load

Halogen/incandescent (230 V)	0–300 W
LED light source/driver (230 V trailing edge)	0–200 VA
LED light source/driver (230 V leading edge)	0–100 VA
Electronic transformers (12 V halogen)	0–300 VA

Do not use with: fluorescent lamps, conventional transformers or low-energy lamps.

#### Support

In the event of any technical questions, please contact our customer service:  
support@plejd.com | +46 (0) 10 203 89 91