

SU S+ 2 x 6 A



### Switching unit SU S+ 2 x 6 A

- Up to 20 luminaires can be monitored individually
- Easy access to fuses
- LED indicates fault and Run/ON for each circuit
- Supplies ballast and LED luminaires
- Service-friendly modular units are wired up and ready to connect to 3-tier 4 mm<sup>2</sup> disconnect neutral terminals

Hybrid operation of maintained light, non-maintained light and switched maintained light per module can be programmed with no additional data cable.

Fusing	10 AT/250 V, 5 x 20
Continuous current rating	6 A per circuit
Max. inrush current	250 A/ms per circuit
Switching time	450 ms
Own consumption	10.5 W (max.)
Module width	6 subunits (H x W x D = 107 x 90 x 58 mm)

10

### Ordering details

Type	Scope of supply	Order No.
SU S+ 2 x 6 A	Switching unit SU S+ 2 x 6 A	40071360350
Spare part	Fuse 10 AT (5 x 20) 250 V (PU 10 pcs.)	40071360483

SOU S+ 2 x 4 A



### Switching over unit SOU S+ 2 x 4 A

- Up to 20 luminaires can be monitored individually
- Separate AV-feed for rental current
- Easy access to fuses
- LED indicates fault and Run/ON for each circuit
- Supplies ballast and LED luminaires
- Service-friendly modular units are wired up and ready to connect to 3-tier 4 mm<sup>2</sup> disconnect neutral terminals inside the distribution box

Hybrid operation of maintained light, non-maintained light and switched maintained light in a single circuit can be programmed with no additional data cable.

Fusing	8 AT/250 V, 6.3 x 32
Continuous current rating	4 A per circuit
Max. inrush current	250 A/ms per circuit
Switching time	450 ms
Own consumption	9 W (max.)
Module width	10 subunits (H x W x D = 178 x 108 x 60 mm)

### Ordering details

Type	Scope of supply	Order No.
SOU S+ 2 x 4 A	Switching over unit SOU S+ 2 x 4 A	40071360461
Spare part	Fuse 8 AT (6.3 x 32) 250 V (PU 10 pcs.)	40071360484