

Tender text Article number 353-702021

Presence detector P41LR, 230 V, secondary, 32-37 m, IP54, for surface mounting, white



Proposed functionalities description according to BIPS 4.7.9

Presence detector P41LR, 230 V, secondary, 32-37 m, IP54, for surface mounting, white

SPECIFICATIONS

Configuration secondary
Detector technology PIR

 $\begin{array}{ll} \mbox{Mounting method} & \mbox{surface mounting} \\ \mbox{Input voltage} & 230 \mbox{ Vac \pm 10 \%, 50 \mbox{ Hz}} \\ \mbox{Detector output} & 230 \mbox{ V (ON/OFF)} \end{array}$

Detection angle 360°

Detection range (PIR) ø 37 m from a height of 3 m

 $\begin{array}{lll} \mbox{Ambient temperature} & -25 - +40 \ ^{\circ}\mbox{C} \\ \mbox{Mounting height} & 2 - 3.5 \ \mbox{m} \\ \mbox{Marking} & \mbox{CE} \\ \mbox{Protection degree} & \mbox{IP54} \end{array}$

Proposed functionalities description according to BIPS 4.7.10

Mounting method

The detector is suitable for surface mounting on all types of ceilings.

Configuration app

All detectors in the installation can be configured using the app and 2-way Bluetooth® communication between a smartphone or tablet and the detector. There are no additional configuration tools required.

PIN code

The detector can be protected with a 4-digit PIN code in the app to prevent others from controlling the detector or modifying its settings.

Event log

The event log in the app shows all the changes you made to the settings of a specific detector.



Sensitivity

The detector's sensitivity for detecting movement can be set using the app and 2-way Bluetooth® communication between a smartphone or tablet and the detector. The 360° detection range can be divided into three sectors each covering 120°. The sensitivity of these sectors can be set separately in 4 levels and a sector can be switched off completely.

Documentation

Documentation is available in digital format and is stored in an online portal.

Detection range

The detection range is documented in accordance with EN/IEC 63180.