ETHERMA°
EFFICIENT. ELECTRIC. HEATING.

PRODUCT DATASHEET

Type: ET-111A
Art. Nr.: 36758

9120015729282

Short description
Radio receiver, 16A, surface mount



Product Description
The ET-111A radio receiver, in conjunction with the ET-14A radio room thermostat, enables simple switching of heating or cooling devices. The 868 MHz frequency range guarantees a long range and optimum connection. The ET-111A switches 16 A and can be mounted on the wall or a flush-mounted box 100 / 100. Switching current: 16 A, dimensions: 140x54x25 mm, protection class: IP 20, transmission frequency: 868 MHz, range 100 - 300 m, CE compliant.

ETIM 10 Characteristics

Suitable for dimmer	✖	**Power consumption**	3680 Watt
Suitable for pulse button	✖	**Number of relays**	1
Suitable for roller shutter switch	✖	**RAL-number (similar)**	9010
Suitable for venetian shutter switch	✖	**Radio frequency**	868 Megahertz
Suitable for venetian-/roller shutter switch	✖	**Code length (Bit)**	0
Suitable for switch	✖	**Number of commands**	0
In housing	✔		
In tube base housing	✖		
Printed circuit board/module	✖		
Current supply	230 V AC		
Push button mode	✖		
Switching mode	✔		
With manual radio transmitter	✖		
With radio coding device	✖		
With radio controlled push button	✖		
Mounting method	Surface mounted		
Material	Plastic		
Material quality	Thermoplastic		
Halogen free	✔		
Surface protection	Untreated		
Surface finishing	Matt		
Type of fastening	Other		
Colour	White		
Transparent	✖		
Suitable for degree of protection (IP)	IP20		
Degree of protection (NEMA)	Other		
Modulation	FM		
Rolling code system	✖		

Created on: 14/09/2026

ETHERMA Elektrowärme GmbH
Landesstrasse 16
A-5302 Henndorf am Wallersee
Tel.: +43 6214 / 76 77
Mail: office@etherma.com
Web: www.etherma.com

ETHERMA Deutschland GmbH
Bahnhofstraße 40
D-48599 Gronau
Tel.: +49 2562 / 81 97 00
Mail: office.de@etherma.com
Web: www.etherma.com

Compatible with Apple HomeKit	✖
Compatible with Google Assistant	✖
Compatible with Amazon Alexa	✖
IFTTT support available	✖