

SKU CG 2 x 3 A



SKU CG 2 x 3 A

Change-over module SKU, module without STAR Function

- Up to 20 luminaires can be monitored individually
- AC/DC switching per each circuit
- Separate fusing for mains and battery operation
- Easy access to fuses
- LED indicates fault and Run/ON for each circuit
- Supplies electronic ballast and LED-luminaires
- Service-friendly modular units are wired up and ready to connect to 3-tier 4 mm² disconnect neutral terminals (optional)
- Gear tray mounting

Fusing	5 AT / 6.3 x 32
Continuous current rating	3 A per circuit
Max. inrush current	120 A per circuit
Typical switch over time	AC/DC approx. 450 ms
Own consumption	3.85 W

Ordering details

Type	Scope of supply	Order No.
SKU	Circuit change over module SKU CG 2 x 3 A	40071347290
Spare part	Fuse 5 AT (6.3 x 32), PU: 10 pcs.	40071689047

SKU CG 1 x 6 A



SKU CG 1 x 6 A

Change-over module SKU, module without STAR Function

- Up to 20 luminaires can be monitored individually
- Separate fusing for mains and battery operation
- Easy access to fuses
- LED indicates fault and Run/ON
- Supplies electronic ballast and LED luminaires
- Service-friendly modular units are wired up and ready to connect to 4 mm² 3-tier disconnect neutral terminals (optional)
- Gear tray mounting

Fusing	10 AT / 6.3 x 32
Continuous current rating	6 A per circuit
Max. inrush current	180 A per circuit
Typical switch over time	AC/DC approx. 450 ms
Own consumption	3.85 W

Ordering details

Type	Scope of supply	Order No.
SKU	Circuit change over module SKU CG 1 x 6 A	40071347346
Spare part	Fuse 10 AT (6.3 x 32), PU: 10 pcs.	40071070715