

SKU CG-S 4 x 1,5 A



SKU CG-S 4 x 1,5 A

Hybrid operation of maintained light, non-maintained light and switched maintained light per module can be programmed with no additional data cable.

- Up to 20 luminaires can be monitored individually
- AC/DC switching per module
- Easy access to fuses
- LED indicates fault and Run/ON for each circuit
- Supplies electronic ballast and LED luminaires
- Service-friendly modular units are wired up and ready to connect to 3-tier 4 mm² disconnect neutral terminals (optional)
- Gear tray mounting

Fusing	2.5 AT / 6.3 x 32
Continuous current rating	1.5 A per circuit
Max. inrush current*	60 A per circuit/240 A per module
Typical switch over time	AC/DC approx. 450 ms
Own consumption	7.7 W

* Example: For two circuits => 120 A per circuit
For four circuits => 60 A per circuit

Ordering details

Type	Scope of supply	Order No.
SKU	Circuit change over module SKU CG-S 4 x 1.5 A	40071347840
Spare part	Fuse 2.5 AT (6.3 x 32), PU: 10 pcs.	40071070716

SKU CG-S 2 x 3 A



SKU CG-S 2 x 3 A

Hybrid operation of maintained light, non-maintained light and switched maintained light in a single circuit can be programmed with no additional data cable.

- Up to 20 luminaires can be monitored individually
- AC/DC switching per each circuit
- Separate fusing for mains and battery operation
- Easy access to fuses
- LED indicates fault and Run/ON for each circuit
- Supplies electronic ballast and LED-luminaires
- Service-friendly modular units are wired up and ready to connect to 3-tier 4 mm² disconnect neutral terminals (optional)
- Gear tray mounting

Fusing	5 AT / 6.3 x 32
Continuous current rating	3 A per circuit
Max. inrush current	250 A per circuit
Typical switch over time	AC/DC approx. 450 ms
Own consumption	3.85 W

Ordering details

Type	Scope of supply	Order No.
SKU	Circuit change over module SKU CG-S 2 x 3 A	40071347051
Spare part	Fuse 5.0 AT (6.3 x 32), PU: 10 pcs.	40071689047