

Base for a two-pole switch, two-pole control switch or two-pole pull switch, 10 A, plug-in terminals

170-71215

10 A
250 Vac

CE

4 year warranty

Mechanism for a two-pole switch, a two-pole control switch or a two-pole pull switch, with screw fixing. With a two-pole switch, you can switch a lamp or several lamps connected in parallel on and off. A finishing set and faceplate in the colour of your choice must be ordered separately.

This article is protected by at least one patent (or patent application). For more info on patents, see www.niko.eu/innovation.

- wire is fixed firmly due to the high-quality plug-in terminal with a long life span, tested according to the norm
- since the conductor release on the mechanisms is located at the front, the wiring cannot push on the release when you place it in the flush-mounting box.

Faster and easier installation:

- all connections terminals are located at the top of the base:


Niko quality:

- long life span since the plug-in terminal stays within the limits of the norm during a temperature and power drop
- metal base is held firmly in place, even on uneven walls, doesn't break and is not subject to stress cracking (small ruptures)

Technical data

Base for a two-pole switch, two-pole control switch or two-pole pull switch, 10 A, plug-in terminals.

- Function:
 - switch
 - block-shaped silver contacts (cadmium-free) in the form of a cross
- Type of control: switch
- Number of buttons: 1
- Number of leds: 0



- Protection degree: IP41 for the combination of a mechanism, central plate and faceplate
- Impact resistance: the combination of a mechanism, a central plate and a faceplate has an impact-resistance of IK06
- SBL load: 100 W
- Material base insert:
 - ureumformaldehyde (UF) with high heat resistance
 - white RAL9010 (approximately)
- Flush-mounting frame type:
 - 1 mm-thick metal
 - galvanized on all sides after cutting, even on the cut edges
 - with 4 grooves with screw hole of 7 mm
 - with 4 screw holes (indicated by a screw symbol) with a diameter of 3 mm for mounting on panels
- Minimum flush-mounting depth: 18 mm
- Required type of flush-mounting box:
 - depth: min. 40 mm (cabling space included)
 - claw/screw fixing: 60 mm
 - inner diameter box: 60 mm
 - multiple boxes centre distance horizontal: 71 mm
 - multiple boxes centre distance vertical: 71 mm
 - multiple boxes centre distance vertical: 60 mm for Belgium and France
- Type of fastening:
 - with screws for simple fixing in a flush-mounting box with grip surfaces
- Centre-to-centre distance:
 - horizontal coupling and vertical coupling with centre-to-centre distance 71 mm
 - horizontal connection of several bases is quick and perfect thanks to the folded-up dovetails on the left and right side
 - extra robustness due to the folded-up edges on the outside of the base and the continuation to the inside of the base
- Base end border: 4 rectangular openings (7 x 2.5 mm) which, if the flush-mounting box protrudes from the plasterwork, can compensate for a margin of between 1 and 1.2 mm, so that the faceplate can still butt up perfectly against the wall
- Terminal wire connection: plug-in terminals
- Terminals location: top of the base
- Terminals wire capacity: 2 x 2.5 mm²
- Suitable type of wire: rigid (solid or stranded)
- Markings on the flush-mounting frame:
 - indelibly indicated at the rear side: stripping length and wiring diagram
 - indelibly indicated at the front side: terminals and switch symbol
- Wire stripping length: 8 mm
- Recess for indication led:
 - the base is provided with 2 rectangular recesses for an optional lighting unit
 - left recess (front view): optional lighting unit with wires can be clicked in
- Minimum ambient temperature: 5 °C
- Maximum ambient temperature: 40 °C
- Dimensions (HxWxD): 73 mm x 73 mm
- Certification marks: CEBEC, DEMKO, NF, KEMA, SEMKO, ÖVE, VDE
- Marking: CE

Wiring diagram

