

Surface-mounting RF receiver with 2 channels, 12-24V AC or DC

05-335

4 year warranty

This surface-mounting receiver has 4 operating modes. You can connect one external impulse push button per channel. You may only use the device for switching low-voltage loads. The device has the following applications:

- ON/OFF via a 2-button function;
- ON when pressed and held, via push button function;
- control of roller blinds or shutters via 2-button function.

The roller blind and shutter function may only be supplied with direct current (DC).



Technical data

Surface-mounting RF receiver with 2 channels, 12-24V AC or DC

- Possible applications include: ON/OFF via a 2-button function, push-button functions 2-button roller blind or shutter function
- Mostly in combination with sun blinds, ventilation or window decoration
- power supply voltage: 12-24 Vac or Vdc
- maximum contact load: AC - 24V, 1 A (24 VA); DC - 30 V, 1 A (30 W)
- Not compatible with the wireless bridge
- Communication protocol: Easywave®
- Operating frequency: 868.3 GHz
- Dimensions (HxWxD): 63 x 70 x 35 mm
- Marking: CE

