

Eaton.com

Protective Devices Miniature Circuit Breakers PLSM, PLZM

Catalog



EATON

Powering Business Worldwide

SG67811



Description

- High-quality miniature circuit breakers for commercial and residential applications
- Contact position indicator red - green
- Guide for secure terminal connection
- 3-position DIN rail clip, permits removal from existing busbar system
- Comprehensive range of accessories can be mounted subsequently
- Rated currents up to 63 A
- Tripping characteristics B, C, D
- Rated breaking capacity 10 kA according to IEC/EN 60898-1

SG48411

Rated current
 I_n (A)Type
DesignationArticle No. Units per
package**10 kA, Characteristic B****1-pole**

6	PLSM-B6	242174	12/120
10	PLSM-B10	242176	12/120
13	PLSM-B13	242178	12/120
16	PLSM-B16	242180	12/120
20	PLSM-B20	242181	12/120
25	PLSM-B25	242182	12/120
32	PLSM-B32	242183	12/120
40	PLSM-B40	242184	12/120
50	PLSM-B50	242185	12/120
63	PLSM-B63	242186	12/120

SG49211

**1+N-pole 1.5MU**

6	PLSM-B6/1N	242243	8/80
10	PLSM-B10/1N	242245	8/80
13	PLSM-B13/1N	242247	8/80
16	PLSM-B16/1N	242249	8/80
20	PLSM-B20/1N	242250	8/80
25	PLSM-B25/1N	242251	8/80
32	PLSM-B32/1N	242252	8/80

SG52711



Rated current I_n (A)	Type Designation	Article No.	Units per package
1+N-pole 2 MU			
6	PLZM-B6/1N	242304	1/60
10	PLZM-B10/1N	242306	1/60
13	PLZM-B13/1N	242308	1/60
16	PLZM-B16/1N	242310	1/60
20	PLZM-B20/1N	242311	1/60
25	PLZM-B25/1N	242312	1/60
32	PLZM-B32/1N	242313	1/60
40	PLZM-B40/1N	242314	1/60
50	PLZM-B50/1N	242315	1/60
63	PLZM-B63/1N	242316	1/60

SG54811



2-pole			
6	PLSM-B6/2	242373	1/60
10	PLSM-B10/2	242375	1/60
13	PLSM-B13/2	242377	1/60
16	PLSM-B16/2	242379	1/60
20	PLSM-B20/2	242380	1/60
25	PLSM-B25/2	242381	1/60
32	PLSM-B32/2	242382	1/60
40	PLSM-B40/2	242383	1/60
50	PLSM-B50/2	242384	1/60
63	PLSM-B63/2	242385	1/60

SG63111



Rated current
 I_n (A)

Type
Designation

Article No.

Units per
package

3-pole

6	PLSM-B6/3	242442	1/40
10	PLSM-B10/3	242444	1/40
13	PLSM-B13/3	242446	1/40
16	PLSM-B16/3	242448	1/40
20	PLSM-B20/3	242449	1/40
25	PLSM-B25/3	242450	1/40
32	PLSM-B32/3	242451	1/40
40	PLSM-B40/3	242452	1/40
50	PLSM-B50/3	242453	1/40
63	PLSM-B63/3	242454	1/40

SG65611

**3+N-pole**

6	PLSM-B6/3N	242511	1/30
10	PLSM-B10/3N	242513	1/30
13	PLSM-B13/3N	242515	1/30
16	PLSM-B16/3N	242517	1/30
20	PLSM-B20/3N	242518	1/30
25	PLSM-B25/3N	242519	1/30
32	PLSM-B32/3N	242520	1/30
40	PLSM-B40/3N	242521	1/30
50	PLSM-B50/3N	242522	1/30
63	PLSM-B63/3N	242523	1/30

SG67811



Rated current I_n (A)	Type Designation	Article No.	Units per package
4-pole			
6	PLSM-B6/4	242580	1/30
10	PLSM-B10/4	242582	1/30
13	PLSM-B13/4	242584	1/30
16	PLSM-B16/4	242586	1/30
20	PLSM-B20/4	242587	1/30
25	PLSM-B25/4	242588	1/30
32	PLSM-B32/4	242589	1/30
40	PLSM-B40/4	242590	1/30
50	PLSM-B50/4	242591	1/30
63	PLSM-B63/4	242592	1/30

SG48411



Rated current
 I_n (A)

Type
Designation

Article No. Units per
package

10 kA, Characteristic C

1-pole

6	PLSM-C6	242200	12/120
10	PLSM-C10	242202	12/120
13	PLSM-C13	242204	12/120
16	PLSM-C16	242206	12/120
20	PLSM-C20	242207	12/120
25	PLSM-C25	242208	12/120
32	PLSM-C32	242209	12/120
40	PLSM-C40	242210	12/120
50	PLSM-C50	242211	12/120
63	PLSM-C63	242212	12/120

SG49211



1+N-pole 1.5MU

6	PLSM-C6/1N	242266	8/80
10	PLSM-C10/1N	242268	8/80
13	PLSM-C13/1N	242270	8/80
16	PLSM-C16/1N	242272	8/80
20	PLSM-C20/1N	242273	8/80
25	PLSM-C25/1N	242274	8/80
32	PLSM-C32/1N	242275	8/80

SG52711



Rated current I_n (A)	Type Designation	Article No.	Units per package
1+N-pole 2 MU			
6	PLZM-C6/1N	242330	1/60
10	PLZM-C10/1N	242332	1/60
13	PLZM-C13/1N	242334	1/60
16	PLZM-C16/1N	242336	1/60
20	PLZM-C20/1N	242337	1/60
25	PLZM-C25/1N	242338	1/60
32	PLZM-C32/1N	242339	1/60
40	PLZM-C40/1N	242340	1/60
50	PLZM-C50/1N	242341	1/60
63	PLZM-C63/1N	242342	1/60

SG54811



2-pole			
6	PLSM-C6/2	242399	1/60
10	PLSM-C10/2	242401	1/60
13	PLSM-C13/2	242403	1/60
16	PLSM-C16/2	242405	1/60
20	PLSM-C20/2	242406	1/60
25	PLSM-C25/2	242407	1/60
32	PLSM-C32/2	242408	1/60
40	PLSM-C40/2	242409	1/60
50	PLSM-C50/2	242410	1/60
63	PLSM-C63/2	242411	1/60

SG63111



Rated current
 I_n (A)

Type
Designation

Article No.

Units per
package

3-pole

6	PLSM-C6/3	242468	1/40
10	PLSM-C10/3	242470	1/40
13	PLSM-C13/3	242472	1/40
16	PLSM-C16/3	242474	1/40
20	PLSM-C20/3	242475	1/40
25	PLSM-C25/3	242476	1/40
32	PLSM-C32/3	242477	1/40
40	PLSM-C40/3	242478	1/40
50	PLSM-C50/3	242479	1/40
63	PLSM-C63/3	242480	1/40

SG65611

**3+N-pole**

6	PLSM-C6/3N	242537	1/30
10	PLSM-C10/3N	242539	1/30
13	PLSM-C13/3N	242541	1/30
16	PLSM-C16/3N	242543	1/30
20	PLSM-C20/3N	242544	1/30
25	PLSM-C25/3N	242545	1/30
32	PLSM-C32/3N	242546	1/30
40	PLSM-C40/3N	242547	1/30
50	PLSM-C50/3N	242548	1/30
63	PLSM-C63/3N	242549	1/30

SG67811



Rated current I_n (A)	Type Designation	Article No.	Units per package
4-pole			
6	PLSM-C6/4	242606	1/30
10	PLSM-C10/4	242608	1/30
13	PLSM-C13/4	242610	1/30
16	PLSM-C16/4	242612	1/30
20	PLSM-C20/4	242613	1/30
25	PLSM-C25/4	242614	1/30
32	PLSM-C32/4	242615	1/30
40	PLSM-C40/4	242616	1/30
50	PLSM-C50/4	242617	1/30
63	PLSM-C63/4	242618	1/30

SG48411



Rated current
 I_n (A)

Type
Designation

Article No.

Units per
package

10 kA, Characteristic D

1-pole

6	PLSM-D6	242223	12/120
10	PLSM-D10	242225	12/120
13	PLSM-D13	242227	12/120
16	PLSM-D16	242229	12/120
20	PLSM-D20	242230	12/120
25	PLSM-D25	242231	12/120
32	PLSM-D32	242232	12/120
40	PLSM-D40	242233	12/120

SG49211



1+N-pole 1.5MU

6	PLSM-D6/1N	242286	8/80
10	PLSM-D10/1N	242288	8/80
13	PLSM-D13/1N	242290	8/80
16	PLSM-D16/1N	242292	8/80
20	PLSM-D20/1N	242293	8/80
25	PLSM-D25/1N	242294	8/80

SG52711



Rated current I_n (A)	Type Designation	Article No.	Units per package
1+N-pole 2 MU			
6	PLZM-D6/1N	242353	1/60
10	PLZM-D10/1N	242355	1/60
13	PLZM-D13/1N	242357	1/60
16	PLZM-D16/1N	242359	1/60
20	PLZM-D20/1N	242360	1/60
25	PLZM-D25/1N	242361	1/60
32	PLZM-D32/1N	242362	1/60
40	PLZM-D40/1N	242363	1/60

SG54811



2-pole			
6	PLSM-D6/2	242422	1/60
10	PLSM-D10/2	242424	1/60
13	PLSM-D13/2	242426	1/60
16	PLSM-D16/2	242428	1/60
20	PLSM-D20/2	242429	1/60
25	PLSM-D25/2	242430	1/60
32	PLSM-D32/2	242431	1/60
40	PLSM-D40/2	242432	1/60

SG63111



Rated current
 I_n (A)

Type
Designation

Article No.

Units per
package

3-pole

6	PLSM-D6/3	242491	1/40
10	PLSM-D10/3	242493	1/40
13	PLSM-D13/3	242495	1/40
16	PLSM-D16/3	242497	1/40
20	PLSM-D20/3	242498	1/40
25	PLSM-D25/3	242499	1/40
32	PLSM-D32/3	242500	1/40
40	PLSM-D40/3	242501	1/40

SG65611

**3+N-pole**

6	PLSM-D6/3N	242560	1/30
10	PLSM-D10/3N	242562	1/30
13	PLSM-D13/3N	242564	1/30
16	PLSM-D16/3N	242566	1/30
20	PLSM-D20/3N	242567	1/30
25	PLSM-D25/3N	242568	1/30
32	PLSM-D32/3N	242569	1/30
40	PLSM-D40/3N	242570	1/30

SG67811



Rated current I_n (A)	Type Designation	Article No.	Units per package
4-pole			
6	PLSM-D6/4	242629	1/30
10	PLSM-D10/4	242631	1/30
13	PLSM-D13/4	242633	1/30
16	PLSM-D16/4	242635	1/30
20	PLSM-D20/4	242636	1/30
25	PLSM-D25/4	242637	1/30
32	PLSM-D32/4	242638	1/30
40	PLSM-D40/4	242639	1/30

Specifications | Miniature Circuit Breakers PLS..., PLZ...

Description

- High selectivity between MCB and back-up fuse due to low let-through energy
- Compatible with standard busbar
- Twin-purpose terminal (lift/open-mouthed) above and below
- Busbar positioning optionally above or below
- Meets the requirements of insulation co-ordination, distance between contacts ≥ 4 mm, for secure isolation
- Suitable for applications up to 48 V DC (use PLS6-DC for higher DC voltages)


Accessories:

Auxiliary switch for subsequent installation	ZP-IHK	286052
	ZP-WHK	286053
Tripping signal switch for subsequent installation	ZP-NHK	248437
Remote control and automatic switching device	Z-FW/LP	248296
Shunt trip release	ZP-ASA/..	248438, 248439
Undervoltage release	Z-USA/..	248288-248291
Additional terminal 35 mm ²	BB-UL-TEPA/35	169823
Switching interlock	Z-IS/SPE-1TE	274418
Neutral disconnect	Z-NTS	248443


Technical Data

		PLS..., PLZ...
Electrical		
Design according to		IEC/EN 60898-1
Current test marks as printed onto the device		
Rated voltage	U_n	AC: 230/400 V DC: 48 V (per pole, max. 2 poles)
Rated frequency		50/60 Hz
Rated breaking capacity according to IEC/EN 60898-1 PLSM, PLZM	I_{cn}	10 kA
Characteristic		B, C, D
Back-up fuse PLSM, PLZM		max. 125 A gL
Selectivity class		3
Endurance		
electrical components		$\geq 10,000$ switching operations
mechanical components		$\geq 20,000$ switching operations
Line voltage connection		at will (above/below)
Mechanical		
Frame size		45 mm
Device height		80 mm
Device width		17.5 mm per pole (1MU) 26.3 mm: device 1P+N (1.5MU)
Mounting		quick fastening with 3 lock-in positions on DIN rail IEC/EN 60715
Degree of protection		IP20
Upper and lower terminals		open-mouthed/lift terminals
Terminal protection		finger and hand touch safe, DGUV VS3, EN 50274
Terminal capacity (1p+N, 1,5TE)		1-25 mm ² 1-25 mm ² / 1-16 mm ² (N)
Terminal torque (1p+N, 1,5TE)		2-2.4 Nm 2-2.4 Nm / 1.2-1.5 Nm (N)
Busbar thickness		0.8 - 2 mm (except N 0.5MU)
Mounting		independent of position
Operation temperature		-25°C to +75°C
Storage- and transport temperature		-40°C up to +75°C

Connection diagrams




Dimensions (mm)




Tripping Characteristics (IEC/EN 60898-1)


Tripping characteristic B



Tripping characteristic C



Tripping characteristic D




Quick-acting (B), slow (C), very slow (D)

Effect of the Ambient Temperature on Thermal Tripping Behaviour

Adjusted rated current values according to the ambient temperature

I _n [A]	Ambient temperature T [°C]															
	-25	-20	-10	0	10	20	30	35	40	45	50	55	60	65	70	75
0.16	0.20	0.19	0.19	0.18	0.17	0.17	0.16	0.16	0.15	0.15	0.15	0.14	0.14	0.14	0.14	0.13
0.25	0.31	0.30	0.29	0.28	0.27	0.26	0.25	0.25	0.24	0.24	0.23	0.23	0.22	0.22	0.21	0.21
0.5	0.61	0.60	0.58	0.56	0.54	0.52	0.50	0.49	0.48	0.47	0.46	0.45	0.44	0.43	0.42	0.41
0.75	0.92	0.90	0.87	0.84	0.81	0.78	0.75	0.74	0.73	0.71	0.69	0.68	0.66	0.65	0.64	0.62
1	1.2	1.2	1.2	1.1	1.1	1.0	1.0	0.99	0.97	0.95	0.93	0.90	0.89	0.87	0.85	0.83
1.5	1.8	1.8	1.7	1.7	1.6	1.6	1.5	1.5	1.5	1.4	1.4	1.4	1.3	1.3	1.3	1.2
1.6	2.0	1.9	1.9	1.8	1.7	1.7	1.6	1.6	1.5	1.5	1.5	1.4	1.4	1.4	1.4	1.3
2	2.4	2.4	2.3	2.2	2.2	2.1	2.0	2.0	1.9	1.9	1.9	1.8	1.8	1.7	1.7	1.7
2.5	3.1	3.0	2.9	2.8	2.7	2.6	2.5	2.5	2.4	2.4	2.3	2.3	2.2	2.2	2.1	2.1
3	3.7	3.6	3.5	3.4	3.3	3.1	3.0	3.0	2.9	2.8	2.8	2.7	2.7	2.6	2.5	2.5
3.5	4.3	4.2	4.1	3.9	3.8	3.7	3.5	3.4	3.4	3.3	3.2	3.2	3.1	3.0	3.0	2.9
4	4.9	4.8	4.7	4.5	4.3	4.2	4.0	3.9	3.9	3.8	3.7	3.6	3.5	3.5	3.4	3.3
5	6.1	6.0	5.8	5.6	5.4	5.2	5.0	4.9	4.8	4.7	4.6	4.5	4.4	4.3	4.2	4.1
6	7.3	7.2	7.0	6.7	6.5	6.3	6.0	5.9	5.8	5.7	5.6	5.4	5.3	5.2	5.1	5.0
8	9.8	9.6	9.3	9.0	8.7	8.4	8.0	7.9	7.7	7.6	7.4	7.2	7.1	6.9	6.8	6.6
10	12	12	12	11	11	10	10	9.9	9.7	9.5	9.3	9.0	8.9	8.7	8.5	8.3
12	15	14	14	13	13	13	12	12	12	11	11	11	11	10	10	10
13	16	16	15	15	14	14	13	13	13	12	12	12	12	11	11	11
15	18	18	17	17	16	16	15	15	15	14	14	14	13	13	13	12
16	20	19	19	18	17	17	16	16	15	15	15	14	14	14	14	13
20	24	24	23	22	22	21	20	20	19	19	19	18	18	17	17	17
25	31	30	29	28	27	26	25	25	24	24	23	23	22	22	21	21
32	39	38	37	36	35	33	32	32	31	30	30	29	28	28	27	26
40	49	48	47	45	43	42	40	39	39	38	37	36	35	35	34	33
50	61	60	58	56	54	52	50	49	48	47	46	45	44	43	42	41
63	77	76	73	71	68	66	63	62	61	60	58	57	56	55	53	52

Load Capacity of Series Connected Miniature Circuit Breakers



Effect of Power Frequency

Effect of power frequency on the tripping behaviour I_{MA} of the quick release


	Power frequency f [Hz]						
	16 ² / ₃	50	60	100	200	300	400
I _{MA} (f)/I _{MA} (50 Hz) [%]	91	100	101	106	115	134	141

The use of the products in networks with other frequencies than 50/60 Hz is in the customer's responsibility.

Short-circuit Selectivity PLSM towards DII-DIV fuse link

In case of short-circuit, there is selectivity between the miniature circuit breakers PLSM and the upstream fuses up to the specified values of the selectivity limit current I_s [kA] (i. e. in case of short-circuit currents I_{ks} under I_s only the MCB will trip, in case of short-circuit currents above this value both protective devices will respond).

*) basically in accordance with EN 60898-1 D.5.2.b



Short-circuit selectivity **Characteristic B** towards fuse link **DII-DIV***)

PLSM I_n [A]	DII-DIV gL/gG								
	10	16	20	25	35	50	63	80	100
1.0	<0.5 ¹⁾	1.2	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
1.5	<0.5 ¹⁾	1.0	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
2.0	<0.5 ¹⁾	<0.5 ¹⁾	0.8	1.6	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
2.5	<0.5 ¹⁾	<0.5 ¹⁾	0.8	1.5	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
3.0	<0.5 ¹⁾	<0.5 ¹⁾	0.8	1.4	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
3.5	<0.5 ¹⁾	<0.5 ¹⁾	0.7	1.3	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
4	<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.0	3.6	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
5	<0.5 ¹⁾	<0.5 ¹⁾	0.6	0.9	2.0	3.5	8.5	10.0 ²⁾	10.0 ²⁾
6		<0.5 ¹⁾	0.6	0.9	1.8	3.2	7.4	10.0 ²⁾	10.0 ²⁾
8		<0.5 ¹⁾	0.5	0.8	1.6	2.6	5.2	8.3	10.0 ²⁾
10			0.5	0.8	1.4	2.2	3.9	6.0	10.0 ²⁾
13			0.5	0.7	1.3	2.0	3.6	5.4	10.0 ²⁾
16				0.6	1.2	1.9	3.2	4.6	8.4
20					1.2	1.8	3.1	4.4	7.8
25					1.2	1.8	3.0	4.2	7.3
32						1.7	2.8	3.9	6.8
40							2.7	3.8	6.5
50							2.5	3.5	5.7
63									5.3

Short-circuit selectivity **Characteristic C** towards fuse link **DII-DIV***)

PLSM I_n [A]	DII-DIV gL/gG								
	10	16	20	25	35	50	63	80	100
0.75	1.0	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
1.0	<0.5 ¹⁾	1.2	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
1.5	<0.5 ¹⁾	<0.5 ¹⁾	1.0	2.2	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
2.0	<0.5 ¹⁾	<0.5 ¹⁾	0.8	1.6	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
2.5	<0.5 ¹⁾	<0.5 ¹⁾	0.8	1.4	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
3.0	<0.5 ¹⁾	<0.5 ¹⁾	0.8	0.9	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
3.5	<0.5 ¹⁾	<0.5 ¹⁾	0.6	0.9	2.2	4.5	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
4	<0.5 ¹⁾	<0.5 ¹⁾	0.6	0.8	1.8	3.6	9.7	10.0 ²⁾	10.0 ²⁾
5	<0.5 ¹⁾	<0.5 ¹⁾	0.6	0.7	1.5	2.7	7.3	10.0 ²⁾	10.0 ²⁾
6		<0.5 ¹⁾	0.5	0.6	1.4	2.4	5.5	10.0 ²⁾	10.0 ²⁾
8		<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.3	2.2	4.7	8.7	10.0 ²⁾
10			<0.5 ¹⁾	0.6	1.3	2.0	3.6	5.4	10.0 ²⁾
13					1.3	1.9	3.3	5.0	9.4
16					1.2	1.8	3.2	4.4	8.0
20					1.2	1.8	3.1	4.1	7.0
25						1.7	2.8	3.8	6.5
32							2.7	3.7	6.2
40								3.5	5.9
50									5.5
63									

Short-circuit selectivity **Characteristic D** towards fuse link **DII-DIV***)

PLSM I_n [A]	DII-DIV gL/gG								
	10	16	20	25	35	50	63	80	100
0.5	0.5	3.0	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
1.0	<0.5 ¹⁾	<0.5 ¹⁾	1.0	2.4	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
1.5	<0.5 ¹⁾	<0.5 ¹⁾	0.7	1.2	3.5	7.7	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
2.0	<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.0	2.8	5.8	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
2.5	<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.4	2.3	4.6	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
3.0	<0.5 ¹⁾	<0.5 ¹⁾	0.6	0.9	2.3	4.3	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
3.5	<0.5 ¹⁾	<0.5 ¹⁾	0.6	0.9	2.1	4.0	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
4		<0.5 ¹⁾	0.6	0.9	2.0	3.8	9.5	10.0 ²⁾	10.0 ²⁾
5		<0.5 ¹⁾	0.5	0.7	1.7	3.1	7.0	10.0 ²⁾	10.0 ²⁾
6			0.5	0.7	1.5	2.6	5.3	9.1	10.0 ²⁾
8			<0.5 ¹⁾	0.7	1.4	2.2	3.9	6.0	10.0 ²⁾
10				0.7	1.2	1.9	3.4	5.0	9.5
13					1.2	1.8	3.2	4.6	8.6
16						1.6	2.7	4.0	7.4
20						1.5	2.5	3.5	6.7
25							2.4	3.4	6.2
32								2.8	5.0
40									4.8

¹⁾ Selectivity limit current I_s under 0.5 kA


²⁾ Selectivity limit current I_s = rated breaking capacity I_{cn} of the MCB

Darker areas: no selectivity

Short-circuit Selectivity PLSM towards D01-D03 fuse link

In case of short-circuit, there is selectivity between the miniature circuit breakers PLSM and the upstream fuses up to the specified values of the selectivity limit current I_s [kA] (i. e. in case of short-circuit currents I_{ks} under I_s only the MCB will trip, in case of short-circuit currents above this value both protective devices will respond).

*) basically in accordance with EN 60898-1 D.5.2.b



Short-circuit selectivity **Characteristic B** towards fuse link **D01-D03***)

PLSM	D01-D03 gL/gG									
I_n [A]	10	16	20	25	35	50	63	80	100	
1.0	<0.5 ¹⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
1.5	<0.5 ¹⁾	4.1	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
2.0	<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.0	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
2.5	<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.0	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
3.0	<0.5 ¹⁾	<0.5 ¹⁾	0.5	1.0	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
3.5	<0.5 ¹⁾	<0.5 ¹⁾	0.5	0.9	7.0	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
4	<0.5 ¹⁾	<0.5 ¹⁾	0.5	0.9	2.5	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
5		<0.5 ¹⁾	0.5	0.8	1.7	4.0	7.0	10.0 ²⁾	10.0 ²⁾	
6		<0.5 ¹⁾	0.5	0.8	1.6	3.6	6.0	10.0 ²⁾	10.0 ²⁾	
8			0.5	0.8	1.4	2.8	4.3	8.2	10.0 ²⁾	
10			0.5	0.7	1.3	2.4	3.4	6.0	10.0 ²⁾	
13			<0.5 ¹⁾	0.7	1.2	2.3	3.2	5.3	10.0 ²⁾	
16				0.6	1.1	2.2	2.9	4.6	10.0	
20					1.1	2.1	2.8	4.4	9.3	
25					1.1	2.0	2.7	4.2	8.7	
32						2.0	2.6	4.0	8.0	
40							2.5	3.8	7.5	
50							2.3	3.4	6.7	
63									6.2	

Short-circuit selectivity **Characteristic C** towards fuse link **D01-D03***)

PLSM	D01-D03 gL/gG									
I_n [A]	10	16	20	25	35	50	63	80	100	
0.75	<0.5 ¹⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
1.0	<0.5 ¹⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
1.5	<0.5 ¹⁾	0.5	0.6	0.9	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
2.0	<0.5 ¹⁾	<0.5 ¹⁾	0.5	0.7	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
2.5	<0.5 ¹⁾	<0.5 ¹⁾	0.5	0.7	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
3.0	<0.5 ¹⁾	<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.9	5.2	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
3.5	<0.5 ¹⁾	<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.8	4.7	9.5	10.0 ²⁾	10.0 ²⁾	
4	<0.5 ¹⁾	<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.6	4.0	7.6	10.0 ²⁾	10.0 ²⁾	
5		<0.5 ¹⁾	<0.5 ¹⁾	0.5	1.3	3.1	5.7	10.0 ²⁾	10.0 ²⁾	
6		<0.5 ¹⁾	<0.5 ¹⁾	<0.5 ¹⁾	1.2	2.7	4.5	10.0 ²⁾	10.0 ²⁾	
8		<0.5 ¹⁾	<0.5 ¹⁾	<0.5 ¹⁾	1.2	2.5	4.0	8.6	10.0 ²⁾	
10			<0.5 ¹⁾	<0.5 ¹⁾	1.2	2.3	3.1	5.4	10.0 ²⁾	
13					1.1	2.2	3.0	4.9	10.0 ²⁾	
16					1.1	2.1	2.8	4.4	9.5	
20					1.0	2.0	2.6	4.0	8.3	
25						1.9	2.5	3.8	7.8	
32							2.5	3.7	7.3	
40								3.5	7.0	
50									6.5	
63										

Short-circuit selectivity **Characteristic D** towards fuse link **D01-D03***)

PLSM	D01-D03 gL/gG									
I_n [A]	10	16	20	25	35	50	63	80	100	
0.5	<0.5 ¹⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
1.0	<0.5 ¹⁾	<0.5 ¹⁾	0.7	1.3	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
1.5	<0.5 ¹⁾	<0.5 ¹⁾	0.6	0.9	2.8	9.0	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
2.0	<0.5 ¹⁾	<0.5 ¹⁾	0.6	0.8	2.2	6.7	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
2.5	<0.5 ¹⁾	<0.5 ¹⁾	0.5	0.7	1.9	5.4	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	
3.0	<0.5 ¹⁾	<0.5 ¹⁾	0.5	0.7	1.8	4.8	9.3	10.0 ²⁾	10.0 ²⁾	
3.5	<0.5 ¹⁾	<0.5 ¹⁾	0.5	0.7	1.7	4.7	8.6	10.0 ²⁾	10.0 ²⁾	
4		<0.5 ¹⁾	0.5	0.7	1.7	4.6	7.7	10.0 ²⁾	10.0 ²⁾	
5		<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.5	3.5	5.8	10.0 ²⁾	10.0 ²⁾	
6			<0.5 ¹⁾	0.5	1.3	2.9	4.5	9.0	10.0 ²⁾	
8			<0.5 ¹⁾	0.5	1.2	2.4	3.5	6.0	10.0 ²⁾	
10				0.5	1.1	2.2	3.0	5.0	10.0 ²⁾	
13					1.1	2.1	2.9	4.6	10.0 ²⁾	
16						1.9	2.6	3.9	9.0	
20						1.7	2.3	3.5	8.0	
25							2.2	3.4	7.5	
32								2.9	6.0	
40									5.7	

¹⁾ Selectivity limit current I_s under 0.5 kA


²⁾ Selectivity limit current I_s = rated breaking capacity I_{cn} of the MCB

Darker areas: no selectivity

Short-circuit Selectivity PLSM towards NH-00 fuse link

In case of short-circuit, there is selectivity between the miniature circuit breakers PLSM and the upstream fuses up to the specified values of the selectivity limit current I_s [kA] (i. e. in case of short-circuit currents I_{ks} under I_s only the MCB will trip, in case of short-circuit currents above this value both protective devices will respond).

*) basically in accordance with EN 60898-1 D.5.2.b

Short-circuit selectivity **Characteristic B** towards fuse link **NH-00***)

PLSM I_n [Å]	NH-00 gL/gG											
	16	20	25	32	35	40	50	63	80	100	125	160
1.0	0.9	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
1.5	0.8	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
2.0	<0.5 ¹⁾	0.5	1.0	2.5	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
2.5	<0.5 ¹⁾	0.5	1.0	2.3	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
3.0	<0.5 ¹⁾	0.5	0.9	2.1	8.0	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
3.5	<0.5 ¹⁾	0.5	0.9	1.8	5.5	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
4	<0.5 ¹⁾	<0.5 ¹⁾	0.8	1.3	2.3	4.3	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
5	<0.5 ¹⁾	<0.5 ¹⁾	0.7	1.1	1.6	2.2	3.6	4.8	8.9	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
6	<0.5 ¹⁾	<0.5 ¹⁾	0.7	1.1	1.5	2.0	3.3	4.3	7.6	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
8	<0.5 ¹⁾	<0.5 ¹⁾	0.6	1.0	1.3	1.7	2.6	3.3	5.2	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
10		<0.5 ¹⁾	0.6	0.9	1.2	1.5	2.2	2.7	4.0	9.0	10.0 ²⁾	10.0 ²⁾
13		<0.5 ¹⁾	0.6	0.8	1.1	1.4	2.1	2.6	3.8	7.9	10.0 ²⁾	10.0 ²⁾
16			0.5	0.7	1.0	1.3	1.9	2.4	3.4	6.4	9.3	10.0 ²⁾
20				0.7	1.0	1.3	1.9	2.4	3.3	6.0	8.7	10.0 ²⁾
25				0.7	1.0	1.3	1.8	2.3	3.2	5.7	8.0	10.0 ²⁾
32					0.9	1.2	1.7	2.2	3.1	5.4	7.6	10.0 ²⁾
40								2.1	3.0	5.1	7.2	10.0 ²⁾
50								1.9	2.8	4.7	6.6	9.5
63										4.4	6.3	8.6

Short-circuit selectivity **Characteristic C** towards fuse link **NH-00***)[illegible]Short-circuit selectivity **Characteristic D** towards fuse link **NH-00*)**

PLSM I_n [A]	NH-00 g/L/GG											
	16	20	25	32	35	40	50	63	80	100	125	160
0.5	2.1	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾
1.0	<0.5 ⁽¹⁾	0.6	1.4	4.3	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾
1.5	<0.5 ⁽¹⁾	<0.5 ⁽¹⁾	0.9	1.6	2.7	4.0	8.0	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾
2.0	<0.5 ⁽¹⁾	<0.5 ⁽¹⁾	0.8	1.3	2.1	3.1	6.0	8.6	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾
2.5	<0.5 ⁽¹⁾	<0.5 ⁽¹⁾	0.7	1.2	1.8	2.6	4.8	6.9	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾
3.0	<0.5 ⁽¹⁾	<0.5 ⁽¹⁾	0.7	1.1	1.7	2.4	4.3	6.0	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾
3.5	<0.5 ⁽¹⁾	<0.5 ⁽¹⁾	0.7	1.1	1.7	2.4	4.2	5.6	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾
4	<0.5 ⁽¹⁾	<0.5 ⁽¹⁾	0.7	1.0	1.6	2.2	3.8	5.2	10.0	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾
5		<0.5 ⁽¹⁾	0.6	0.9	1.4	1.9	3.2	4.1	7.1	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾
6		<0.5 ⁽¹⁾	0.5	0.8	1.2	1.6	2.6	3.3	5.5	10.0 ⁽²⁾	10.0 ⁽²⁾	10.0 ⁽²⁾
8			0.5	0.8	1.1	1.5	2.2	2.7	4.1	8.7	10.0 ⁽²⁾	10.0 ⁽²⁾
10			0.5	0.7	1.0	1.3	1.9	2.5	3.6	7.2	10.0 ⁽²⁾	10.0 ⁽²⁾
13					1.0	1.3	1.9	2.3	3.4	6.5	9.5	10.0 ⁽²⁾
16						1.1	1.6	2.0	3.0	5.5	8.0	10.0 ⁽²⁾
20							1.4	1.8	2.8	5.0	7.5	10.0 ⁽²⁾
25								1.8	2.7	4.8	7.0	10.0 ⁽²⁾
32									2.4	4.1	6.2	9.3
40										4.0	6.0	9.0

¹⁾ Selectivity limit current I_s under 0.5 kA


2) Selectivity limit current I_c = rated breaking capacity I_{cn} of the MCB

Darker areas: no selectivity

Short-circuit Selectivity PLSM towards cylindrical fuse links

In case of short-circuit, there is selectivity between the miniature circuit breakers PLSM and the upstream fuses up to the specified values of the selectivity limit current I_s [kA] (i. e. in case of short-circuit currents I_{ks} under I_s only the MCB will trip, in case of short-circuit currents above this value both protective devices will respond).

*) basically in accordance with EN 60898-1 D.5.2.b



Short-circuit selectivity **Characteristic B** towards fuse link **CH10x38 gG, CH14x51 gG, CH22x58 gG*)**)

PLSM I_n [A]	CH10x38 gG				CH15x51 gG					CH22x58 gG								
	16	20	25	32	20	25	32	40	50	16	20	25	32	40	50	63	80	100
1	0.5	>10	>10	>10	>10	>10	>10	>10	>10	1.2	>10	>10	>10	>10	>10	>10	>10	>10
2	<0.5	0.6	1.2	3.6	0.5	1.0	5.2	>10	>10	<0.5	0.5	1.1	>10	>10	>10	>10	>10	>10
3	<0.5	0.5	0.8	1.4	0.5	0.9	3.7	>10	>10	<0.5	0.5	1.0	8.0	>10	>10	>10	>10	>10
4	<0.5	<0.5	0.7	1.2	<0.5	0.7	1.7	4.0	>10	<0.5	<0.5	0.8	2.3	5.1	>10	>10	>10	>10
6	<0.5	<0.5	0.6	0.9	<0.5	0.7	1.3	2.0	2.7	<0.5	<0.5	0.7	1.5	2.2	2.6	5.6	10	>10
10	<0.5	<0.5	0.6	0.9	<0.5	0.6	1.1	1.5	2.0	<0.5	<0.5	0.6	1.2	1.6	1.9	3.2	4.8	9.0
13	<0.5	<0.5	0.6	0.8	<0.5	0.6	1.0	1.4	1.9	<0.5	<0.5	0.6	1.2	1.5	1.7	3.0	4.3	7.7
16		<0.5	0.5	0.8	<0.5	0.5	1.0	1.4	1.8		<0.5	0.5	1.1	1.4	1.6	2.7	3.8	6.3
20			0.5	0.8		<0.5	0.9	1.3	1.6			0.5	1.1	1.4	1.6	2.6	3.7	6.0
25				0.7			0.9	1.3	1.6				1.0	1.3	1.5	2.5	3.5	5.6
32								1.2	1.5					1.3	1.5	2.4	3.3	5.2
40									1.5						1.4	2.3	3.2	5.0
50																2.1	2.9	4.5
63																	2.8	4.2

Short-circuit selectivity **Characteristic C** towards fuse link **CH10x38 gG, CH14x51 gG, CH22x58 gG*)**)

PLSM I_n [A]	CH10x38 gG				CH15x51 gG					CH22x58 gG								
	16	20	25	32	20	25	32	40	50	16	20	25	32	40	50	63	80	100
0.5	1.9	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10
1	<0.5	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10
2	<0.5	0.6	1.2	3.6	0.5	1.0	4.5	>10	>10	<0.5	0.6	1.1	>10	>10	>10	>10	>10	>10
3	<0.5	0.5	0.8	1.4	<0.5	0.7	1.4	2.4	3.7	<0.5	<0.5	0.8	1.8	2.7	3.5	9.3	>10	>10
4	<0.5	<0.5	0.7	1.2	<0.5	0.7	1.2	2.0	2.9	<0.5	<0.5	0.7	1.5	2.2	2.7	6.7	>10	>10
6	<0.5	<0.5	0.6	0.9	<0.5	<0.5	1.0	1.4	2.0	<0.5	<0.5	0.6	1.1	1.6	1.9	4.2	7.0	>10
10	<0.5	<0.5	0.5	0.8	<0.5	<0.5	0.9	1.3	1.7	<0.5	<0.5	0.6	1.1	1.5	1.8	2.9	4.1	7.5
13	<0.5	<0.5	0.5	0.8	<0.5	<0.5	0.9	1.3	1.7	<0.5	<0.5	0.5	1.0	1.4	1.7	2.7	3.8	6.5
16		<0.5	0.5	0.8	<0.5	<0.5	0.8	1.2	1.6		<0.5	<0.5	1.0	1.3	1.5	2.6	3.5	5.8
20			<0.5	0.7		<0.5	0.8	1.2	1.5			<0.5	0.9	1.2	1.4	2.5	3.3	5.4
25				0.7			0.8	1.1	1.4				0.9	1.2	1.4	2.3	3.2	5.0
32								1.1	1.4					1.1	1.3	2.2	3.0	4.8
40									1.3						1.2	2.0	2.8	4.6
50																1.9	2.6	4.2
63																	2.3	3.7

Short-circuit selectivity **Characteristic C** towards fuse link **CH10x38 gG, CH14x51 gG, CH22x58 gG*)**)

PLSM I_n [A]	CH10x38 gG				CH15x51 gG					CH22x58 gG								
	16	20	25	32	20	25	32	40	50	16	20	25	32	40	50	63	80	100
0.5	0.9	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10
1	<0.5	>10	>10	>10	>10	>10	>10	>10	>10	<0.5	0.6	1.5	>10	>10	>10	>10	>10	>10
2	<0.5	0.5	0.6	1.6	<0.5	1.0	1.7	>10	>10	<0.5	0.5	0.8	2.1	3.3	4.3	>10	>10	>10
3	<0.5	<0.5	0.8	1.3	<0.5	0.7	1.4	2.4	3.4	<0.5	<0.5	0.7	1.7	2.5	3.2	8.2	>10	>10
4	<0.5	<0.5	0.7	1.2	<0.5	0.7	1.3	2.0	3.1	<0.5	<0.5	0.7	1.6	2.3	3.0	7.0	>10	>10
6	<0.5	<0.5	0.6	1.0	<0.5	<0.5	1.0	1.6	2.0	<0.5	<0.5	0.6	1.3	1.7	2.1	4.2	7.0	>10
10	<0.5	<0.5	0.6	0.8	<0.5	<0.5	0.9	1.3	1.7	<0.5	<0.5	0.5	1.1	1.4	1.6	2.8	4.1	7.1
13	<0.5	<0.5	0.5	0.8	<0.5	<0.5	0.9	1.3	1.6	<0.5	<0.5	0.5	1.0	1.4	1.6	2.7	3.8	6.5
16		<0.5	0.5	0.7	<0.5	<0.5	0.8	1.1	1.4		<0.5	<0.5	1.0	1.2	1.4	2.3	3.2	5.5
20			<0.5	0.7		<0.5	0.7	1.0	1.3			<0.5	0.8	1.1	1.3	2.1	2.9	4.6
25				0.7			0.7	1.0	1.2				0.8	1.0	1.2	2.0	2.8	4.0
32														0.9	1.0	1.7	2.3	3.8
40															1.0	2.0	2.2	3.6

Darker areas: no selectivity

Eaton's electrical business is a global leader with deep regional application expertise in power distribution and circuit protection; power quality, backup power and energy storage; control and automation; life safety and security; structural solutions; and harsh and hazardous environment solutions. Through end-to-end services, channel and an integrated digital platform & insights Eaton is powering what matters across industries and around the world, helping customers solve their most critical electrical power management challenges.

For more information, visit [Eaton.com](https://www.eaton.com).



Eaton Industries (Austria) GmbH
Scheydgasse 42
1210 Vienna
Austria

Eaton
EMEA Headquarters
Route de la Longeraie 7
1110 Morges, Switzerland

© 2022 Eaton
All Rights Reserved
Publication No. CA019064EN
Article number 302774-MK
June 2023

The products, information and prices contained in this document are subject to change. The same is true for any errors or omissions. Only the order confirmation and the technical documentation received from Eaton are binding. Photos and illustrations are indicative only and do not serve as proof of any appearance or functionality. Their use in any form must be approved in advance by Eaton. The same applies for brand names (in particular Eaton, Moeller, Cutler-Hammer, Cooper and Bussmann). Eaton's terms of sale, as published on Eaton's websites and included with order confirmations received from Eaton, apply.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Follow us on social media to get the latest product and support information.

