


ENSTALL

**ESDEC**

# ClickFit EVO Standing seam roof Manual



**ClickFit**  
Evo  
METAL ROOF

# TABLE OF CONTENTS

<b>Introduction</b>	<b>3</b>
About this document	3
Other relevant documents	3
Earthing and bonding	3
Symbols used in this manual	3
<b>Warranty and liability</b>	<b>4</b>
Warranty	4
Maintenance	4
Liability	4
<b>Product information</b>	<b>4</b>
Intended use	4
Improper use	4
Compatible solar panel flange dimensions	4
Specifications	5
<b>System and application</b>	<b>6</b>
Components	6
Application	7
<b>Safety</b>	<b>9</b>
Personal protective equipment	9
Safety warnings and regulations	9
<b>Installation</b>	<b>10</b>
1. Preparation	10
Tightening torques	10
2. Preparing and sizing mounting rails	13
3. Fixing the seam clamps	15
4. Attaching the mounting rails	16
5. Optional: Attaching the MLPE clips	18
ClickFit EVO MLPE Clip Light Weight	18
ClickFit EVO MLPE Clip Heavy Weight	19
6. Mounting solar panels with 60mm panel clamps	20
Mounting the first panel	20
Mounting the following panels	22
Mounting the last panel	23
7. Mounting the solar panels with 35 mm panel clamps	26
Mounting the first panel	26
Mounting the following panels	29
Mounting the last panel	31
8. Mounting multiple rows	33
<b>Removal and recycling</b>	<b>34</b>
General	34

# INTRODUCTION

## ABOUT THIS DOCUMENT

In this manual you will find the installation instructions for the ClickFit EVO mounting system for solar panels on pitched standing seam roofs.

The system is suitable for mounting solar panels in portrait and landscape orientation.

These instructions are addressed at qualified technical personnel.

You can download the latest version of this manual from [eu.enstall.com](http://eu.enstall.com).

## OTHER RELEVANT DOCUMENTS

When installing the ClickFit EVO mounting system, you will need the following documents:

- The project plan, which you can create in the calculator at <https://eu.enstall.com/en/calculator>.
- The installation manuals for the solar panels, inverters and any other components.
- S-5! Technical information available at [s-5.com/metal-roof-resources](http://s-5.com/metal-roof-resources)

During the installation of the mounting system, it is important to adhere to the installation manual, the installation manual of the components, and the accompanying standards to prevent accidents. Pay special attention to (local) standards, regulations and legislation (among others):

- Local Building Regulations (latest version)
- Health and Safety at Work etc Act 1974
- Health and Safety in Roof work - HSE
- Eurocodes 0 (EN 1990 - Structural Design)
- Eurocodes 1 (EN 1991 - (Influences on structures)
- HD-IEC 60364 series - Electrical installations for low voltage
- EN-IEC 62305-2 - Protection lightning - Risk Management
- MIS 3002 – The solar PV standard
- MCS012 - Product Certification Scheme Requirements: Pitched Roof Installation Kits

## EARTHING AND BONDING

Our ClickFit EVO systems are VDE certified for corrosion and bonding. According to the electrical standard HD-IEC 60364 – chapter 712, functional bonding for inverter's isolation check is necessary.

In the Enstall ClickFit EVO Series, functional bonding is achieved by the EVO 35 mm and 60 mm module clamps, which provide the electrical connection between the module edge and the EVO rails. The final functional bonding connection is made by proper mounting of a separate bonding cable onto the EVO rail and an adequate bonding connection with the inverter or earthing contact.

For detailed instructions on grounding and bonding, consult the electrical standard HD-IEC 60364 and any local regulations. Please, follow the instructions of the inverter's manual. This operation needs to be done by a certified electrician.

## SYMBOLS USED IN THIS MANUAL

	Warning!	Failure to follow this instruction could result in serious injury or major damage to the product.
	Caution!	Failure to follow this instruction could result in personal injury or damage to the product.
	Note	Emphasises an instruction.

## WARRANTY AND LIABILITY

### WARRANTY

The warranty is subject to the warranty terms and general terms & conditions of Enstall. These can be found on the [eu.enstall.com](https://eu.enstall.com) website.

### MAINTENANCE

Please refer to the maintenance checklist at <https://eu.enstall.com/>.

### LIABILITY

The manufacturer accepts no liability for damage or injury caused by the failure to comply (strictly) with the safety guidelines and instructions in this manual, or by negligence during installation of the product and the accessories listed in this document. Enstall reserves the right to change this document without notice.

## PRODUCT INFORMATION

### INTENDED USE

The ClickFit EVO mounting system is designed for mounting solar panels on pitched standing seam roofs. With this mounting system, solar panels can be positioned on the roof either with the short side at the bottom (portrait) or with the long side at the bottom (landscape).


### IMPROPER USE

The mounting system is not suitable for use on types of roof other than the one specified.

### COMPATIBLE SOLAR PANEL FLANGE DIMENSIONS

The Clickfit EVO module clamps are suitable for solar panels with a frame height between 29-50mm and a frame width of at least 12mm, where a sufficient clamping force can be applied.

Check the documentation of the solar panel supplier if the intended solar panel can withstand the loads and clamping force.



## SPECIFICATIONS

Orientation of solar panels	Portrait and landscape	
Maximum area of solar panels	3.92m <sup>2</sup>	
Maximum field size	Horizontal rails: 6.15m per segment	Vertical rails: 15m per segment
Roof type	Pitched roof with seams, except copper roofs	
Roof pitch	5-60°  At an inclination angle of <10°, the self-cleaning effect of the panel is affected.	
Maximum roof height	 Subject to Eurocode guidelines and national additions. Use the calculator to calculate the possibilities of your project.	
Edge zone	The edge zone is not a fixed distance and is indicated in the Enstall calculator. Within this zone, installation is permitted in certain cases, depending on the calculation.	
No-go zone	30cm distance to the ridge, 30cm to the side of the roof and 30 cm to the gutter.	


<sup>1)</sup> Ensure that the module frame is compatible with the ClickFit EVO clamps before installation.

<sup>2)</sup> Always consider the right measures related to fire spread and compartmentalization. This might influence the modules segment size.

-  Enter the data in the calculator, so you are sure of choosing the right system for the terrain category, snow loads and wind zone that applies to your project.
-  Depending on the roof and the result obtained from the calculator, you can lay several segments with solar panels next to each other. Always leave a minimum of 12mm of space between segments to allow for expansion of the roof.
-  If your project has different specifications than these, please contact Enstall.

## SYSTEM AND APPLICATION

### COMPONENTS



Component	Article number
1 ClickFit EVO Seam Clamp	100803_-
2 ClickFit EVO Mounting Rail	10081_-
3 ClickFit EVO Module Clamp universal	1008020(-B)
4 ClickFit EVO 60 Mid Clamp Black	1008021-B
5 ClickFit EVO 60 End Clamp Black	1008022-B
6 ClickFit EVO Mounting Rail End Cap	1008060(-B)
7 ClickFit EVO End Clamp Support	1008065(-B)
8 ClickFit EVO End Cap without end clamp support	1008066(-B)

Accessory	Article number
9 ClickFit EVO Mounting Rail Coupler	1008061
10 ClickFit EVO MLPE Clip Light Weight	1008067
11 ClickFit EVO MLPE Clip Heavy Weight	1008068
12 ClickFit EVO Self-drilling screw 6,3x42mm SW10/T30	1003016
13 ClickFit EVO mounting set	1008064
14 ClickFit EVO Screw Bit Torx 30	1008069



**i** Check that the correct components are present in the required numbers according to the project plan generated by the calculator.

## APPLICATION



seam clamp			
Article number	1008035	1008033	1008031
Suitable for	Single-folded standing seam roof Snap seam roof	Double-folded standing seam roof	Round standing seam roof
Seam opening	14mm	9mm	Ø23mm
Fixing			
Click connection			

**i** Use the calculator to determine the correct rail orientation for your project. The calculator takes into account, for example, the type of roof covering and the structure supporting the roof.

Horizontal rail orientation



Vertical rail orientation



 Mounting solar panels in portrait orientation in combination with vertical rail orientation is not recommended. This mounting method is also not supported by the calculator.

# SAFETY

## PERSONAL PROTECTIVE EQUIPMENT

Hearing protection	Safety helmet	Safety glasses	Face masks	Safety gloves	Safety clothing	Safety shoes

## SAFETY WARNINGS AND REGULATIONS

### Warning!







- Installation work should always be carried out by at least two skilled people.
- Do not use components from other mounting systems.
- Do not leave out parts.
- Always work according to the current regulations for working on roofs.
- Do not perform the installation in strong winds, or when the roof is slippery or wet.
- Always work on the roof with fall protection and, if necessary, with safety nets and edge protection.
- Never stand on or in the gutter.
- Make sure that an aerial platform or ladder does not rest on the seams.
- Always use a lifting aid or hoisting device when moving heavy equipment.
- Always place ladders on a strong, stable surface.

### Caution!

- Walk as little as possible on the roof. Use an aerial platform, ladder or other solution.
- Never walk on the system or on the solar panels.

# INSTALLATION


## 1. Preparation

<b>1</b>	Inspect the roof.				
<input type="checkbox"/>	The roof is in good condition.				
<input type="checkbox"/>	The roof construction has sufficient bearing capacity to support the installation, taking into account wind and snow loads.				
<b>2</b>	Check the project plan and components.				
<input type="checkbox"/>	Check the project plan. Is there no project plan? Then create one in the online calculator before starting installation.				
<input type="checkbox"/>	Check that all components are present (page 5).				
<b>3</b>	Make sure all the required tools are at hand.				
					
Marker or chalk	Brush	Tape measure	Hacksaw	Water pump pliers	Torque wrench up to 20Nm with TR30 safety bit



## TIGHTENING TORQUES

**!** Always use a torque wrench. Make sure that the bit is correctly and completely inserted in the screw head when tightening, in view of the high tightening torque.

Screw	Tightening torque
ClickFit EVO Module Clamp universal	4.5 Nm
ClickFit EVO Mounting Rail Clicker	9 Nm
Mounting screw for vertical rail	1 Nm
Tightening torque for steel standing seam roofs with material thickness > 0.7mm	18-20 Nm
ClickFit EVO MLPE Clip Heavy Weight	8-12 Nm
ClickFit EVO 60 End Clamp Black	16.5 Nm
ClickFit EVO 60 Mid Clamp Black	16.5 Nm

**4** Clean the roof seams**5** Determine the position of the solar panels on the roof

- ! Consider the (local) fire regulations for photovoltaic installations. To mitigate the risk of fire spread, the fire compartments of the object must be respected. The PV system should not be placed over fire partition walls and a minimum distance of 30 cm must be kept. Likewise, it is wise to keep space in relation to skylights, lighting globes, corners and potential fire hazards.
- ! Develop a project plan using the Enstall calculator and adhere to its guidelines. Access the calculator at [calculator.eu.enstall.com](http://calculator.eu.enstall.com).
- ! The distance from the edge of solar panels to both the ridge and the gutter must be at least 30cm.
- ! The distance from the solar panels to the side of the roof must be at least 30cm.
- i Take into account sunlight and shade over the whole year. If necessary, use a power optimizer or micro inverter to get the most out of your installation.




**6** Draw the lines and end points for the mounting rails


- i** Consult the project plan to determine the position of the mounting rails for your panel.
- i** When needed, rail spacing can be extended to the previous or next tile, crest or seam, up to 400 mm beyond the recommended distance. Enstall recommends to always respect the module manufacturers' rail spacing and clamping specifications.
- i** For pitched roofs, we recommend a horizontal mounting. This is more durable and often creates a neater finish.
- i** Rail lengths can be found in the project plan.

For mounting in landscape orientation, the mounting rails should be placed at around  $\frac{1}{4}$  of the short sides of the panel.

For mounting in portrait orientation, the mounting rails should be placed at around  $\frac{1}{4}$  of the long sides of the panel.

**7** Mark the position of the seam clamps


- !** If you can see the position of the standing seam clips, mount the seam clamps at least 50mm away.
- i** Consult the project plan to determine the position of the seam clamps for your project.




## 2. Preparing and sizing mounting rails

- 1 Consult the project plan for the overall layout of the solar panel segments.
- 2 Calculate the full length of the solar panel layout, accounting for gaps and/or spacing.
- 3 Calculate the necessary mounting rail extensions and adjustments.

**i** Measure the solar panels and add 12mm between each solar panel for the universal module clamp (20mm for the ClickFit EVO 60mm clamp). Add 20-35mm on each side for mounting the end clamp and end cap (50-70mm for the ClickFit EVO 60mm clamp).




**4** Use couplers to connect the mounting rails, if necessary

**5** If the overhang is greater than 350mm: extend the mounting rail to the next flange.


**6** Cut the mounting rails to size.

a. If the calculated overhang is less than 350mm beyond the marked position of the last seam clamp, keep 20-35mm rail length overhang for mounting the end cap (art. no. 1008066(-B)) (>40mm for the ClickFit EVO 60mm clamp).




b. If the calculated overhang of the solar panel is **more** than 350mm beyond the marked position of the last flange clamp, mark the position of an extra flange clamp on the nearest flange. Extend the mounting rail to 50mm beyond the extra flange clamp.

**i** The additional 50 mm extension allows for proper fitting of an end cap (art. no. 1008066(-B)) to the mounting rails.



### 3. Fixing the seam clamps

#### 1 Place the clamp on the seam




1008035


1008033

1008031

#### 2 Tighten the screw




#### 3 Rotate the click connection into the correct orientation




#### 4. Attaching the mounting rails

- 1 Place the mounting rail into the click connection and align them




- 2 Click in the mounting rails



**3** For vertical mounting: Secure the mounting rails to the click connections

**i** First secure the bottom click connection with a self-drilling screw. Skip two click connections and then screw down the fourth click connection. Repeat until the top click connection.




## 5. Optional: Attaching the MLPE clips


### CLICKFIT EVO MLPE CLIP LIGHT WEIGHT

- 1 Click the Light Weight MLPE clip onto the rail
- 2 Click the optimiser on the Light Weight MLPE clip

**i** Use one MLPE clip per solar panel.



**i** With vertical rail orientation you have to fix the MLPE clip by bending the edge of the mounting rail with adjustable pliers.




**CLICKFIT EVO MLPE CLIP HEAVY WEIGHT**

- 1 Attach the optimiser to the heavy weight MLPE clip
- 2 Click the heavy weight MLPE clip onto the rail

**i** For larger optimizers (equipped with 2 slots), it is essential to use two Heavy Weight MLPE clips.


**i** With vertical rail orientation you have to fix the cable clip by bending the edge of the mounting rail with adjustable pliers.




## 6. Mounting solar panels with 60mm panel clamps

### MOUNTING THE FIRST PANEL


1 Optional: Click the Auxiliary set on the panel.




2 Optional: Click the cables of the panel firmly into the cable clamp.




3 Slide the end caps onto the rails.




4 Click the ClickFit EVO 60 End Clamps on the rails.





5 Optional: Guide the cables of the solar panel through the click connections.



6 Place the panel on the rails and Slide the panel against the clamps.



7 Fasten the screw of the end clamps to secure the panel. Apply a torque of 16.5 Nm.





#### MOUNTING THE FOLLOWING PANELS




Optional: Repeat steps 6.1. and 6.2.: "Click the Auxiliary set on the panel" and "Click the cables of the panel firmly into the cable clamp".


8 Click the 60mm Mid clamps on the rails.



9 Place the next panel on the rails and slide the panel against the clamps.



10 Fasten the screw of the mid clamps to secure the panel. Apply a torque of 16.5 Nm.



Repeat the steps in this chapter for all panels of the row.


### MOUNTING THE LAST PANEL

<input type="checkbox"/>	Optional: Repeat steps 6.1. and 6.2.: "Click the Auxiliary set on the panel" and "Click the cables of the panel firmly into the cable clamp".
<input type="checkbox"/>	Repeat steps 6.8. and 6.9.: "Click the 60mm Mid clamps on the rails." and "Place the next panel on the rails and slide the panel against the clamps.".

**11** Optional: saw the mounting rails to size


- If the overhang is **less** than 350 mm beyond the last seam clamp, keep a rail overhang of 50 - 70 mm for mounting the end cap (art. no. 1008066(-B)).
- If the overhang is **more** than 350 mm beyond the last seam clamp, install an extra seam clamp. Extend the mounting rail to at least 50 mm beyond the extra seam clamp and attach the mounting rail to it.

The extra 50 mm provides sufficient length to fit an end cap (art. no. 1008066(-B)) to the mounting rails.




**12** Click the ClickFit EVO 60 End Clamps on the rails.

**13** Fasten the screw of the end clamps to secure the panel. Apply a torque of 16.5 Nm.




14 Slide the end caps onto the rails.




## 7. Mounting the solar panels with 35 mm panel clamps

### MOUNTING THE FIRST PANEL


1 Optional: Click the Auxiliary set on the panel.





2 Optional: Click the cables of the panel firmly into the cable clamp.





3 Click the 35mm module clamp on the rails.




**4** Slide the end caps onto the rails.**5** Rotate the upper part of the module clamp over the end cap.**6** Optional: Guide the cables of the solar panel through the click connections.

7 Place the panel on the rails and Slide the panel against the clamps.




8 Screw the clamps onto the panel. Apply a torque of 4.5 Nm.



**MOUNTING THE FOLLOWING PANELS**


**9** Click the universal module clamp on the rails.

**i** Install the module clamp with the drainage channel of the module clamp pointing downwards.




**□** Optional: Repeat steps 1. and 2.: "Click the Auxiliary set on the panel" and "Click the cables of the panel firmly into the cable clamp".

**10** Place the next panel on the rails and slide the panel against the clamps.



**11** Screw the clamps onto the panel. Apply a torque of 4.5 Nm.



Repeat the steps in this chapter for all panels of the row.


## MOUNTING THE LAST PANEL

<input type="checkbox"/>	Optional: Repeat steps 1. and 2.: "Click the Auxiliary set on the panel" and "Click the cables of the panel firmly into the cable clamp".
<input type="checkbox"/>	Repeat steps 1. and 2.: "Click the universal module clamp on the rails." and "Place the next panel on the rails and slide the panel against the clamps.".


### 12 Optional: saw the mounting rails to size

- If the overhang is **more** than 350 mm beyond the last seam clamp, install an extra seam clamp. Extend the mounting rail to at least 50 mm beyond the extra seam clamp and attach the mounting rail to it.
- If the overhang is smaller than 350 mm, keep a minimum of 20 mm to a maximum of 35 mm rail length overhang for mounting the end cap (art. no.1008060(-B)).


The extra 50mm provides sufficient length to fit an end cap (article no. 1008066(-B)) to the mounting rails. For the end clamp, use the end clamp support (article no. 1008065(-B)).




13 Click the universal module clamp on the rails.




2x




14 Slide the end caps onto the rails.




2x



15 Rotate the upper part of the module clamp over the end cap.



16 Screw the clamps onto the panel. Apply a torque of 4.5 Nm.




## 8. Mounting multiple rows

- 1 Mount each next row against the previous row

**i** Always keep a minimum of 12 mm between each row of panels in the case of horizontal rails, or each panel column in the case of vertical rails.

**i** Always follow the project plan from the calculator.



## REMOVAL AND RECYCLING

### GENERAL

Always follow local laws and regulations when dismantling the mounting system and disposing of it.