Motion detector, 230 V, 26 m, round, for flush-mounting box, white

351-25065



The motion detector with one channel for flush-mounting in ceilings is suitable for switching indoor lighting on and off. You can always activate the light with a NO push button (230 V AC) (to be ordered separately). The detector is equipped with an integrated light sensor. Finishing colour: white


- The presence detector for each large room
- Can be placed at a height of up to 8 metres
- Separate setting for the lux, the switch-off delay and the sensitivity
- Low consumption (0.25 W)
- Surface-mounting boxes available separately

The motion detector for large meeting rooms, hangars, etc.

- The lighting remains on while there is motion
- You can programme it manually or using the optional remote control
- You can always be certain of excellent detection thanks to the three PIR sensors.



Detection range



B Towards
nowards
ø 10 m
ø 13 m
ø 14 m
ø 15 m















flushmountir




Technical data

Article number	351 - 25065
Input voltage	230 Vac \pm 10 %, 50 Hz
Detector output	230 V (ON/OFF)
Maximum MCB rating	10 A (limited by national installation rules)
Relay contact	N.O. (max. 10 A)
Maximum load incandescent and halogen lamps ($\cos \phi = 1$)	2300 W
Maximum load fluorescent lamps ($\cos \phi \ge 0.5$)	1150 VA
Maximum load economy lamps (CFLi)	350 W
Maximum load LED lamps 230 V	350 W
Light intensity range	5 lux – 2000 lux
Number of channels	1 channel
Switch-off delay	pulse, 10 s – 20 min
Detection angle	360 °
Detection range (PIR)	ø 26 m from a height of 3 m
Ambient temperature	-20 − +40 °C
Mounting method	flush-mounting box
Mounting height	2 – 8 m
Dimensions visible (HxWxD)	105 x 105 x 43 mm
Dimensions (HxWxD)	105 x 105 x 79 mm
Protection degree	IP20
Marking	CE

Accessories

351-25420	Surface-mounting box, white
350-41936	Universal remote control for smartphone
351 - 25320	IR remote control
351 - 25310	IR remote control for users

Dimensions



Wiring diagram

