

## Data Sheet | Item Number: 2006-8401

Disconnect plug for carrier terminal blocks; for using a receptacle terminal block as a disconnect terminal block; orange

<https://www.wago.com/2006-8401>



Color: ■ orange

### Electrical data

#### Ratings per IEC/EN

Nominal voltage (III/3)	1500 V
Rated impulse voltage (III/3)	12 kV
Rated current	30 A

### Material data

Note (material data)

[Information on material specifications can be found here](https://www.wago.com/us/material-specifications)

Color	orange
Insulation material	Polyamide (PA66)
Flammability class per UL94	V0
Fire load	0.039 MJ
Weight	3.2 g

### Environmental requirements

Continuous operating temperature	105 °C
----------------------------------	--------

### Commercial data

Product Group	22 (TOPJOB S)
eCl@ss 10.0	27-14-11-92
eCl@ss 9.0	27-14-11-92
ETIM 8.0	EC002848
ETIM 7.0	EC002848
PU (SPU)	48 (12) pcs
Packaging type	Box
Country of origin	DE
GTIN	4050821372479
Customs tariff number	85366990990

### Environmental Product Compliance

RoHS Compliance Status Compliant, No Exemption

### Approvals / Certificates

#### General approvals



Approval	Standard	Certificate Name
CSA DEKRA Certification B.V.	C22.2 No. 158	1543858

#### Declarations of conformity and manufacturer's declarations



Approval	Standard	Certificate Name
Railway WAGO GmbH & Co. KG	-	Railway Ready

### Downloads

#### Environmental Product Compliance

Compliance Search
Environmental Product Compliance 2006-8401 <a href="#">↓</a>

### Documentation

Additional Information		
Technical Section	pdf 2240.62 KB	<a href="#">↓</a>



Bid Text			
2006-8401	19.02.2019	xml 2.57 KB	<a href="#">↓</a>
2006-8401	28.04.2017	doc 23.50 KB	<a href="#">↓</a>

### CAD/CAE-Data

CAD data
2D/3D Models 2006-8401 <a href="#">↓</a>

CAE data
WSCAD Universe 2006-8401 <a href="#">↓</a>

### Installation Notes



Carrier terminal block with disconnect plug (2006-8401) in operating position

Carrier terminal block with disconnect plug (2006-8401) in parked position

Subject to changes. Please also observe the further product documentation!

Current addresses can be found at: [www.wago.com](http://www.wago.com)