

# LED Driver 10 W

LED-10



LED Driver 10 W with built-in dimming function for one or more LED luminaires (150–700 mA) or LED strips (12/24 V DC) for up to 10 W. The product can be controlled wirelessly via the app or through other products from Plejd.

- Dimmable 1–100 %.
- Two inputs for local control, using for example a momentary push button or motion sensor.
- Time functions, such as astro/time schedule.
- Scenes from phone, tablet, or push button.

Install the product in the appliance box behind the push button/box lid or secure it with a Mounting clip (MNT-01, not included) on the wall or DIN rail.


#### Load (CC)

150 mA	1–4 W
350 mA	1–9 W
500 mA	1–10 W
700 mA	1–10 W

#### Load (CV)

12 V (DC)	0–8 W
24 V (DC)	0–10 W

Use only for LED loads (DC).



#### MAINS ELECTRICITY

230 VAC/50 Hz, max 0.15 A

#### STANDBY POWER

No-load power consumption (P<sub>no</sub>): N/A

Standby power consumption (P<sub>sb</sub>): 0.3 W

Networked standby power consumption (P<sub>net</sub>): 0.3 W

#### TOTAL PRODUCT WEIGHT

39 g

#### EFFICIENCY AT FULL-LOAD

83 %

#### EXTERNAL OPERATING TEMPERATURE

-20 to +35 °C

#### DIMENSIONS

46x46x18 mm

#### CABLE AREA

Connections: 0.5–4.0 mm<sup>2</sup>

#### PROTECTION

Overtemperature software  
Short circuit protection

#### POWER FACTOR (PF)

0.6

#### UOUT

3–28 V DC

#### RADIO

2.4 GHz mesh  
Bluetooth®  
<10 dBm

#### RADIO RANGE

Approx. 10 m indoors.  
The Plejd mesh technology extends the range by allowing the units to communicate with each other.