ETHERMA°
EFFICIENT. ELECTRIC. HEATING.

PRODUCT DATASHEET

Type: ET-111C
Art. Nr.: 40039

9120061392454

Short description
Radio receiver for LAVA LITE, in flush-mounted box, 10A



Product Description
The ET-111C radio receiver enables simple switching of electric heaters and underfloor heating systems. The receiver can control the room temperature with the ET-14A and also the floor temperature in conjunction with the ET-EF-111 remote sensor. The 868 MHz frequency range guarantees a long range and optimum connection. Installation in flush-mounted box, switching current: 10 A, dimensions: 50x47x33 mm, protection class: IP 20, transmission frequency: 868 MHz, range 100 - 300 m, CE-compliant.

ETIM 10 Characteristics

Suitable for dimmer	✖	**Power consumption**	2300 Watt
Suitable for pulse button	✖	**Number of relays**	1
Suitable for roller shutter switch	✖	**RAL-number (similar)**	9016
Suitable for venetian shutter switch	✖	**Radio frequency**	868 Megahertz
Suitable for venetian-/roller shutter switch	✖	**Code length (Bit)**	0
Suitable for switch	✔	**Number of commands**	0
In housing	✖		
In tube base housing	✖		
Printed circuit board/module	✔		
Current supply	230 V AC		
Push button mode	✖		
Switching mode	✔		
With manual radio transmitter	✖		
With radio coding device	✖		
With radio controlled push button	✖		
Mounting method	Flush-mounted		
Material	Plastic		
Material quality	Duroplast		
Halogen free	✖		
Surface protection	Untreated		
Surface finishing	Matt		
Type of fastening	Mounting with screw		
Colour	White		
Transparent	✖		
Suitable for degree of protection (IP)	IP20		
Degree of protection (NEMA)	Other		
Modulation	FM		
Rolling code system	✖		

Created on: 14/09/2026

ETHERMA Elektrowärme GmbH
Landesstrasse 16
A-5302 Henndorf am Wallersee
Tel.: +43 6214 / 76 77
Mail: office@etherma.com
Web: www.etherma.com

ETHERMA Deutschland GmbH
Bahnhofstraße 40
D-48599 Gronau
Tel.: +49 2562 / 81 97 00
Mail: office.de@etherma.com
Web: www.etherma.com

Compatible with Apple HomeKit	✖
Compatible with Google Assistant	✖
Compatible with Amazon Alexa	✖
IFTTT support available	✖