

PRODUCT DATASHEET

Type: LAVA-DIMM-LUX
Art. Nr.: 46408



9120129932004

Short description

Dimmer for LAVA-LUX lighting, suitable for all sizes



Product Description

Dimmer for LAVA-LUX lighting, suitable for all sizes

ETIM characteristics

Assembly arrangement	Basic element with complete housing	Number of modules (module system)	0
Method of operation	Radio frequency (RF)	Number of units	1
App control via Bluetooth	✗	RAL-number (similar)	9016
Dimming phase cut-on (leading edge)	✓	Nominal voltage	12 12 Volt
Dimming phase cut-off (trailing edge)	✗	Frequency	50 60 Hertz
Serial dimmer	✗	Control voltage	12 12 Volt
Type of load	Universal	Nominal power resistive load	96 192 Watt
Substation input	✓	Nominal power inductive load	96 192 Voltampere
Light value memory	✓	Nominal power capacitive load	96 192 Voltampere
Applicable with button	✓	Max. switching power LED	0 Watt
Applicable with movement sensor	✓	Power consumption	3.5 Watt
Applicable with presence indicator	✓	Core cross section	1.5 1.5 Square millimetre
Applicable with time switch/timer	✓	Device width	37 Millimetre
Applicable with transmission button	✓	Device height	100 Millimetre
Applicable with infrared button	✗	Device depth	21 Millimetre
Min. brightness controllable	✗	Min. depth of built-in installation box	0 Millimetre
Mounting method	Surface mounted		
Type of fastening	Glue		
Material	Plastic		
Material quality	Thermoplastic		
Halogen free	✗		
Surface protection	Other		
Surface finishing	Matt		
Colour	White		

Created on: 27/06/2025

Transparent	×
Suitable for degree of protection (IP)	IP20
Impact strength	IK01
Connection type	Screw terminal
Compatible with Apple HomeKit	×
Compatible with Google Assistant	×
Compatible with Amazon Alexa	×
IFTTT support available	×