

FICHE TECHNIQUE DU PRODUIT

Type: LAVA-DIMM-LUX
Art. Nr.: 46408



9120129932004

Brève description

Variateur pour éclairage LAVA-LUX, adapté à toutes les tailles



Description du produit

Variateur pour éclairage LAVA-LUX, adapté à toutes les tailles

Caractéristiques de l'ETIM

App control via Bluetooth	×	Number of modules (module system)	0
Dimming phase cut-on (leading edge)	✓	Number of units	1
Dimming phase cut-off (trailing edge)	×	RAL-number (similar)	9016
Serial dimmer	×	Nominal voltage	12 12 Volt
Substation input	✓	Frequency	50 60 Hertz
Light value memory	✓	Control voltage	12 12 Volt
Applicable with button	✓	Nominal power resistive load	96 192 Watt
Applicable with movement sensor	✓	Nominal power inductive load	96 192 Voltampere
Applicable with presence indicator	✓	Nominal power capacitive load	96 192 Voltampere
Applicable with time switch/timer	✓	Max. switching power LED	0 Watt
Applicable with transmission button	✓	Power consumption	3,5 Watt
Applicable with infrared button	×	Core cross section	1,5 1,5 Square millimetre
Min. brightness controllable	×	Device width	37 Millimetre
Material quality	Thermoplastic	Device height	100 Millimetre
Halogen free	×	Device depth	21 Millimetre
Transparent	×	Min. depth of built-in installation box	0 Millimetre
Suitable for degree of protection (IP)	IP20		
Impact strength	IK01		
Compatible with Apple HomeKit	×		
Compatible with Google Assistant	×		
Compatible with Amazon Alexa	×		
IFTTT support available	×		

Créé le: 09/10/2024

FICHE TECHNIQUE DU PRODUIT

Cr    le: 09/10/2024