

PRODUCT DATASHEET

Type: RF-RELAIS-16A
Art. Nr.: 46090



9120105419093

Short description

RF relay 230V / 50Hz 16A in combination with RF thermostat THERM-520RF

**Product Description**

The RF relay fits into any flush-mounted or cavity wall box. Particularly suitable for controlling electric heaters. Can be easily connected to our THERM-520RF wireless thermostat. Voltage: 230V AC / 50Hz, 16 (5) amps, 868.0-868.6MHz;

ETIM characteristics

Suitable for dimmer	×	Power consumption	0.5 Watt
Suitable for pulse button	×	Number of relays	1
Suitable for roller shutter switch	×	RAL-number (similar)	9010
Suitable for venetian shutter switch	×	Radio frequency	868 Megahertz
Suitable for venetian-/roller shutter switch	×	Code length (Bit)	0
Suitable for switch	✓	Number of commands	0
In housing	✓		
In tube base housing	×		
Printed circuit board/module	×		
Current supply	230 V AC		
Push button mode	×		
Switching mode	×		
With manual radio transmitter	×		
With radio coding device	×		
With radio controlled push button	✓		
Mounting method	Surface mounted		
Material	Plastic		
Material quality	Thermoplastic		
Halogen free	✓		
Surface protection	Other		
Surface finishing	Matt		
Type of fastening	Glue		
Colour	White		
Transparent	×		
Suitable for degree of protection (IP)	IP30		
Degree of protection (NEMA)	Other		
Modulation	FM		

Created on: 27/06/2025

Rolling code system	×
Compatible with Apple HomeKit	×
Compatible with Google Assistant	×
Compatible with Amazon Alexa	×
IFTTT support available	×