

PRODUCT DATASHEET

Type: ET-111C
Art. Nr.: 40039



9120061392454

Short description

Radio receiver for LAVA LITE, in flush-mounted box, 10A



Product Description

The ET-111C radio receiver enables simple switching of electric heaters and underfloor heating systems. The receiver can control the room temperature with the ET-14A and also the floor temperature in conjunction with the ET-EF-111 remote sensor. The 868 MHz frequency range guarantees a long range and optimum connection. Installation in flush-mounted box, switching current: 10 A, dimensions: 50x47x33 mm, protection class: IP 20, transmission frequency: 868 MHz, range 100 - 300 m, CE-compliant.

ETIM characteristics

Suitable for dimmer	×	Number of relays	1
Suitable for pulse button	×	RAL-number (similar)	9016
Suitable for roller shutter switch	×	Radio frequency	868 Megahertz
Suitable for venetian shutter switch	×	Code length (Bit)	0
Suitable for venetian-/roller shutter switch	×	Number of commands	0
Suitable for switch	✓		
In housing	×		
In tube base housing	×		
Printed circuit board/module	✓		
Current supply	230 V AC		
Push button mode	×		
Switching mode	✓		
With manual radio transmitter	×		
With radio coding device	×		
With radio controlled push button	×		
Mounting method	Flush-mounted		
Material	Plastic		
Material quality	Duroplast		
Halogen free	×		
Surface protection	Untreated		
Surface finishing	Matt		
Type of fastening	Mounting with screw		
Colour	White		
Transparent	×		
Suitable for degree of protection (IP)	IP20		

Created on: 09/10/2024

PRODUCT DATASHEET

Degree of protection (NEMA)	Other
Modulation	FM
Rolling code system	×
Compatible with Apple HomeKit	×
Compatible with Google Assistant	×
Compatible with Amazon Alexa	×
IFTTT support available	×

Created on: 09/10/2024