

Compact PIR detector - lux sensing. Time delay - IP55. DALI DIM max 20 luminaires  
0041542



## Features

- PIR sensor with switching and dimming capability for controlling up to 20 DALI luminaires. On/off and dim via lux sensing. Absence/presence detection. Adjustable time delay (10sec to 99min). Maintained illuminance capabilities. Up to 7m detection radius at 2.8m mounting height. Programmable via handset. Mounting accessories available. 10A maximum load.

## Product Overview

<b>Product name</b>	Compact PIR detector - lux sensing. Time delay - IP55. DALI DIM max 20 luminaires
<b>Technology</b>	Controls
<b>Max load (A)</b>	10
<b>Mount</b>	Ceiling recessed mounting, Ceiling surface mounting
<b>Input protocol</b>	PIR Sensor, IR Signal, Lux sensor
<b>Output protocol</b>	DALI, DSI
<b>Number of channels</b>	2
<b>Environment</b>	Interior
<b>IP rating</b>	IP40
<b>Product EAN number</b>	5410288415420

Compact PIR detector - lux sensing. Time delay - IP55. DALI DIM max 20  
luminaires

**0041542**

## Technical drawings

