




Read these instructions & save for future use

led ropelight | 230V | 50m | horizon | 3000K WW



Article number **055-108**

Brand **Tronix Lighting**

Type **Ropelights**

Contents of this product **1x 36 led/m 13mm ropelight 50m**

Technical datasheet **Digitally available
on our webshop**



*View instructions and
technical data also on
our website*

TRONIX



Before first use


Before getting started with this product, it is advisable to check the order completeness and any damage. If this is the case, please contact Tronix Lighting.

Description


Light snakes can be used year-round because of their versatility and durability. They are ideal for lighting a pool or patio, as bar decorations, accent structures or any other indoor or outdoor accent lighting.

Features

- Vertical LED structure
- LED type DIP LED
- Includes power cord (schuko EU plug)



Installation



1. Remove the product and associated parts from the packaging. Remove the strip from the reel before using it;
2. Check the set you are using and then cut the light hose to size using the mark on the hose;
3. Attach the light hose using clips (485-060) or a profile (485-160, 485-165 and 485-170). Make sure you have enough space when the light hose goes through a bend. Bend main cores only at right angles to avoid damage;
4. Check the installation and finish the light hose using the termination cap (glue it in place). Then connect the plug to complete the set.



Safety

Safety is a top priority at Tronix Lighting. Therefore, we heartily recommend that you follow the following steps closely:

- Keep this manual carefully for future reference;
- Choose a qualified electrician while installing, maintaining or inspecting this product;
- Never look directly into a light source to avoid possible damage to the eye;
- Always ensure that the relevant power group is on non-active when the product is connected;
- Use only recommended combinations (LED drivers, controllers or dimmers) to avoid injury or damage to the product.

Technical problems and repair

Should a product not work properly after installation, or if the product exhibits problems over time, it is advisable to check the following elements:

- Check the wiring and installation of your product;
- Check for the presence of interfering elements such as dust, water or other electronics;
- If possible, try disconnecting the product and testing it in another location to rule out a problem at the location;
- Should you be dealing with a WIFI-based product, check and reset your router's settings.

Should the product still not work after testing, it is recommended to send it in for inspection and/or repair. To do so, please contact Tronix Lighting using nearby details and proof of purchase (packing slip).



CARE



SHARE



CONNECT

Supplier:

Tronix Lighting B.V

Vluchtoord 41
5406 XP Uden, Netherlands

+31 (0)413 330 380
sales@tronixlighting.com

Terms and symbols (as relevant to product)



The **CE mark** indicates that this product complies with EU regulations on safety, health and environmental protection;



The **WEEE symbol** stands for "Waste Electrical and Electronic Equipment Regulation," a directive on the collection, recycling and recovery of electronic waste;



The **Class II symbol** indicates that this product is double insulated;

- This product has an **IP65 rating**. This means the housing is touch-safe, fully protected from dust and spray-proof (12.5 L/min) regardless of angle.